

Protocol for HL960/HL990



Display : **Informatic mode (code 000)**

Bits per second : **9 600**

Data bits : **8**

Parity : **None**

Stop bits : **1**

Flow control : **Xon / Xoff**

Protocol :	02	L0	09	A_YYY_XX_XX_XX	09	0D	0A
	Hex.	Text	Hex.	Text	Hex.	Hex.	Hex.

02 : **Hexadecimal code**

L0 : **Display 1**

L1 : **Display 2**

L2 : **Display 3**

... : **...**

L9 : **Display 10**

09 : **Hexadecimal code**

YYY : **Bib number**

XX_XX_XX : **Time**

09, 0D, 0A : **Hexadecimal code**



TAG Heuer Professional Timing

Av. des Champs Montants 14a

2074 Marin - Switzerland

tel : + 41 / 32 755 60 00 - fax : + 41 / 32 755 66 82

www.tagheuer-timing.com